

Coaxial High-Pass Filter 6-18GHz

P/N: YX-HPF-6-18GHz

Features

- It can realize the customized design scheme
- High Rejection
- Low Insertion Loss

Typical Applications

- Wireless Infrastructure
- 5G communication
- Test and measurement Instrument



Environmental Specifications					
Parameter		Min.	Тур.	Max.	Units
Pass band frequency		6		18	GHz
Insertion Loss		<u></u>	9	2.0	dB
VSWR		/2		1.8	: 1
Stop band frequency		DC		5.4	GHz
Stop band rejection		50			dB
Power Rating	Power	1 W		w	
Impedance		50			Ohms
Weight		NA			Ounces
Input / Output Connectors		SMA – Female			
Material		Aluminum			
Finish		Oxidation sandblasting			



Coaxial High-Pass Filter 6-18GHz

P/N: YX-HPF-6-18GHz

Environmental Specifications				
Operational Temperature(°C)	-40°C~+70°C			
Storage Temperature (°C)	-55°C~+85°C			
Altitude	30,000 ft. (Epoxy Sealed Controlled environment)			
Aititude	60,000 ft. 1.0psi min (Hermetically Sealed Un-controlled environment)			
Vibration	25gRMS (15 degrees 2KHz) endurance, 1 hour per axis			
Humidity	100% RH at 35°c, 95%RH at 40°c			
Shock	20G for 11msec half sine wave,3 axis both directions			

Outline Drawing:

All Dimensions in mm (inches)Outline Outline Tolerances $\pm 0.5(0.02)$ Mounting Holes Tolerances $\pm 0.2(0.008)$



